

This paper has been submitted to the SIAM Journal of Applied Mathematics under the title

**Bifurcation Analysis for Phase Transitions in Superconducting Rings
with Nonuniform Thickness**

1. INTRODUCTION

Superconductivity is a macroscopic manifestation of quantum mechanics. This is noticeable in Josephson junctions and in the Little-Parks effect [8], where the behavior of a ring is not determined by the local magnetic field, but rather by the magnetic flux which it encloses. In the original Little-Parks experiment, the superconducting sample was a long cylindrical shell, intended to have uniform thickness, embedded in a magnetic field parallel to the axis. The sample ‘does not like’ to enclose a non-integer number of magnetic flux quanta. As a consequence, when the flux deviates from an integer number, the transition to superconductivity occurs at a lower temperature.

Another interesting feature of superconductivity is its globallity. More precisely, a uniform material at uniform temperature will be superconducting at some places and normal at others if this nonuniform pattern minimizes the overall thermodynamic potential. When parts of the sample are normal, while the rest is superconducting, the material is said to be in a mixed state. A known case of mixed state is the “intermediate state” [2, 11] for type I superconductors. In this case normal and superconducting domains of finite volume coexist. Another known case is that of “vortices” [2, 11] for type II superconductors. For each vortex, the material is normal (i.e. the order parameter vanishes) along a line. Using physical arguments and numerical minimizations, we recently predicted [3] a situation in which quantization and globallity give rise to a qualitatively different kind of mixed state. In this case the sample is doubly connected, i.e. homotopic to an annulus, but it is energetically advantageous to break the superconductivity at a suitable layer, so that the superconducting part is singly connected. When this is the situation, we shall say that the sample is in the “singly-connected phase”.

In the present paper we analyze the different kinds of functions that minimize the thermodynamic potential in the Little-Parks experiment. They depend upon the temperature and the magnetic flux, with the deviation from uniform thickness as an additional parameter.

The deviation from uniformity will be usually taken as a perturbation. A complementary analysis is provided by the special case of shells whose thickness is piecewise constant. We shall see that the “phase diagram” (the boundaries between qualitatively different minimizers in the temperature-flux plane) contains several bifurcation lines and critical points. Even an infinitesimal deviation from uniform thickness turns out to produce a qualitative change in the phase diagram. We provide an analytic treatment of the minimization problem near the bifurcation lines and the critical points.

In the next section we formulate our energy functional, define nondimensional quantities and derive the Euler-Lagrange equations. In Section 3 we consider the case of uniform rings and gain some insight into the phase transition picture. Bifurcation lines from the normal state are studied in Section 4. We show that there actually exist two types of bifurcations: one in which the sample becomes superconducting everywhere, and another which involves a mixed (singly-connected) state. The mixed state itself may bifurcate into doubly connected superconducting states. The location of such bifurcations in the parameters plane (magnetic flux and temperature) is found in Section 5.

We show that there exist two critical points where bifurcation lines intersect. Section 6 is devoted to a detailed analysis of the various phases near these points. In Section 7 we summarize our results and discuss them. In particular we propose several experimental setups to verify our theoretical predictions.

2. FORMULATION

We deal with a sample of superconducting material with the topology of a ring. The traditional treatment of the Little-Parks experiment may be found in [11]. Here we develop a formalism which is suited for the case of nonuniform thickness. The free energy of the sample can be expressed by means of the Ginzburg-Landau theory [2], [4], [5], [7]. If we write the order parameter in the form $\psi = ue^{i\phi}$, then the free energy density of the superconducting phase, relative to the normal phase, is

$$g = -\alpha u^2 + \frac{1}{2}\beta u^4 + (H - H_{\text{ext}})^2/(8\pi) + [\hbar^2(\nabla u)^2 + u^2(\hbar\nabla\phi - e^*A/c)^2]/(2m^*). \quad (1)$$

Here $e^*/2$ and $m^*/2$ are the electron charge and mass, $H = \nabla \times A$ is the magnetic field, H_{ext} is the magnetic field which would be present in the absence of superconductivity, $\hbar$ is Planck's constant divided by 2π , c is the speed of light, and α, β are two material parameters. We denote by T_c the critical temperature in the sample without magnetic field and are interested in the region where the temperature T is lower than and close to T_c . The parameter α is proportional to $1 - T/T_c$.

To fix ideas, we shall consider a sample in the form of a cylindrical shell and use cylindrical coordinates (z, r, θ) , with the axis of the coordinates at the axis of the shell. We denote by R the radius of the cylinder (measured up to the middle of the shell) and denote by $D(\theta)$ the area obtained by cutting the shell with a plane of given θ . $D(\theta)$ is the product of the “height” (parallel to the axis) and the “thickness” (along the radial direction). The height will be taken as uniform. In the original Little-Parks experiment, the height was much larger than the thickness; in recent experiments, the height is smaller than the thickness. There are two lengthscales [5] in superconductivity: the magnetic field varies significantly over a lengthscale called the *penetration depth*, given by $\lambda_L = (c/e^*)(m^*\beta/4\pi\alpha)^{1/2}$; the lengthscale over which the order parameter ψ varies significantly is the *coherence length* $\xi = (\hbar^2/2m^*\alpha)^{1/2}$. Since $\alpha \rightarrow 0$ for $T \rightarrow T_c$, both lengthscales are large near T_c . We shall see that the interesting temperatures are those where ξ is comparable with R . We shall take thickness and height much smaller than R , so that ψ becomes a function of θ only. (Also in the original Little-Parks experiment ψ is independent of z , due to translational symmetry.)

Since $H - H_{\text{ext}}$ is proportional to the current along the ring, its contribution to the free energy is proportional to the square of $D(\theta)$, whereas the contribution of the other terms is linear in $D(\theta)$. Therefore, the term with $H - H_{\text{ext}}$ becomes negligible at the interesting temperatures, and will be dropped for simplicity. The contribution of this term will be evaluated in Appendix A and, in particular, we shall have a criterion for the validity of this approximation.

In order to write the free energy in a more convenient form, we observe that the supercurrent I along the ring is given by

$$I = (e^*/m^*)u^2(\hbar\nabla\phi - e^*A/c)D(\theta), \quad (2)$$

and it is independent of θ . Dividing (2) by $u^2 D$, and integrating along the ring, we obtain an alternative representation for the supercurrent,

$$I = 2\pi k \hbar \alpha e^* / (m^* \beta \Lambda). \quad (3)$$

Here

$$k = \frac{1}{2\pi} [\phi(2\pi) - \phi(0)] - \Phi / \Phi_0, \quad (4)$$

Φ is the magnetix flux, $\Phi_0 = 2\pi \hbar c / e^*$ is the flux quantum,

$$\Lambda = R \int_0^{2\pi} y^{-2} D^{-1} d\theta, \quad (5)$$

and we have scaled the order parameter $y = (\beta/\alpha)^{1/2} u$.

We can now use the equality between both expressions for I to get rid of the term with $\nabla\phi$ in (1) and write the energy functional in the form

$$\tilde{G} = \int_{\text{sample}} \frac{\beta g}{\alpha^2 R} = \int_0^{2\pi} [-y^2 + \frac{1}{2} y^4 + (\frac{\xi}{R})^2 (y')^2] D(\theta) d\theta + \frac{(2\pi k \xi)^2}{R \Lambda}. \quad (6)$$

Note that in obtaining (6) we have not actually required any particular shape of the ring. We shall keep this notation with circular appearance for aesthetic reasons, but all our treatment remains valid for an arbitrary loop if we define R as its length divided by 2π and θ as the arc length divided by R . Also for aesthetic reasons, we define $\lambda = (R/\xi)^2$, multiply $\tilde{G}$ by the constant $\lambda / \int_0^{2\pi} D(\theta) d\theta$, take R as the unit of length, and arrive at our model for the free energy

$$G[y, \phi] = \left(\int_0^{2\pi} (-\lambda y^2 + \frac{1}{2} \lambda y^4 + (y')^2) D d\theta + (2\pi k)^2 \Lambda^{-1} \right) / \int_0^{2\pi} D d\theta. \quad (7)$$

A rigorous derivation of (7) as a limit of the Ginzburg-Landau functional in thin rings will be published elsewhere.

While the dependence of G on the amplitude y is quite complex, G depends on the phase ϕ only through k^2 . For a given flux Φ , the phase ϕ will adjust itself to minimize k^2 in (4).

In order to minimize G , the order parameter has to choose between two distinct strategies, each of which gives rise to a constraint.

- *Doubly-connected phase* (DC): The entire sample is superconducting ($y > 0$ for all θ) and the topology of the superconducting region is the same as that of the sample. The constraint is that $[\phi(2\pi) - \phi(0)]/(2\pi)$ must be integer and this condition restricts the minimum value which k^2 can assume for a given Φ . For any Φ , k^2 can be in the interval $[0, \frac{1}{4}]$, and therefore it will be in this interval when G is minimized. The interval $k^2 \leq \frac{1}{4}$ will be dubbed *the relevant region*. However, there is much to be learned by allowing values $k^2 > \frac{1}{4}$ in our model functional G , and we shall study this situation, too. The last term in the numerator of (7) may be regarded as the energy price that superconductivity has to pay for staying doubly-connected and enclosing a noninteger flux.
- *Singly-connected phase* (SC): In this case y vanishes for some θ , so that the superconducting region is singly-connected and does not enclose the magnetic flux. $\phi(2\pi)$ and $\phi(0)$ are now unrelated, so that their difference can adjust itself to yield $k = 0$ in (4) and the last term in the numerator of (7) vanishes. We can also regard this vanishing as due to the divergence of Λ (and then the value of k is actually irrelevant). The constraint is now that y vanishes at some θ , and the energy price is in the first and third term in the integrand in (7). We shall often consider the case in which D is an increasing function of θ for $0 < \theta < \pi$ and is symmetric about $\theta = 0$ and $\theta = \pi$. We shall denote such D 's as *functions of type S*. In this case, the place with the lowest energy price for y to vanish will be at $\theta = 0$.

Our goal is now to find the function y that minimizes G for given values of the parameters λ , which is controlled by the temperature, and k , which is governed by the magnetic flux. In particular, we want to find the values of λ and k for which $y(0)$ vanishes, and how $y(0)$ approaches 0 as these parameters vary. Note that the minimum value of k^2 which is consistent with (4) is a periodic function of the flux. This implies that all physical properties will be periodic functions of the flux. This is a fair idealisation of the experimentally known results.

Minimizing (7) over all periodic functions, we obtain the Euler-Lagrange (EL) equation

$$(Dy')' + \lambda D(y - y^3) - \left(\frac{2\pi k}{\Lambda}\right)^2 \frac{1}{D} y^{-3} = 0. \quad (8)$$

The task of solving Eq. (8) is complicated by the presence of the nonlocal quantity Λ . This reflects the nonlocal nature of the effect we are discussing. For the SC phase the EL equation reduces to

$$(Dy')' + \lambda D(y - y^3) = 0, \quad y(0) = y(2\pi) = 0. \quad (9)$$

It is sometimes more convenient to work with $w = y^2$. We therefore write the functional G and the associated EL equation in terms of w

$$G[w] = \left(\int_0^{2\pi} \left(-\lambda w + \frac{1}{2} \lambda w^2 + \frac{(w')^2}{4w} \right) D d\theta + \frac{(2\pi k)^2}{\Lambda} \right) / \int_0^{2\pi} D d\theta, \quad (10)$$

$$D w w'' + D' w w' - \frac{D}{2} (w')^2 + 2\lambda D w^2 (1 - w) - \frac{2}{D} \left(\frac{2\pi k}{\Lambda} \right)^2 = 0, \quad (11)$$

and now $\Lambda = \int_0^{2\pi} (wD)^{-1} d\theta$. If w vanishes at some point, then, as before, the terms involving Λ are not present. Adding to the numerator of (10) half the integral of (11) divided by w , we obtain that, if the EL equation is fulfilled, then the free energy is

$$G_{\text{EL}} = -\frac{1}{2} \lambda \int_0^{2\pi} D w^2 d\theta / \int_0^{2\pi} D d\theta. \quad (12)$$

This shows that any nontrivial solution of the EL equation has lower free energy than the normal state.

Since G is invariant under multiplication of $D(\theta)$ by a constant, the average of D can be set as 1 without loss of generality. Except for Subsection 4.3, we shall adopt this convention in the following.

3. UNIFORM D AND OUTLINE OF GENERAL D

The case $D=\text{constant}$ is the traditional Little-Parks problem. In this case it is not difficult to guess the solutions of (8) and (9). For the doubly-connected phase we try the ansatz $y=\text{constant}$, which gives

$$w = y^2 = 1 - k^2/\lambda, \quad (13)$$

for which G becomes

$$G_{\text{const}} = -\frac{1}{2} (\lambda - k^2)^2 / \lambda. \quad (14)$$

For the SC phase

$$y = \sqrt{\frac{2m}{1+m}} \operatorname{sn}\left(\sqrt{\frac{\lambda}{1+m}} \theta | m\right), \quad (15)$$

where m obeys

$$K(m) = \pi \sqrt{\frac{\lambda}{1+m}}; \quad (16)$$

this gives the free energy

$$G_{\text{SC}} = \frac{2\lambda}{3(1+m)} \left(-\frac{2+m}{1+m} + \frac{2E(m)}{K(m)} \right). \quad (17)$$

In the equations above, sn is a Jacobian elliptic function and K and E are complete elliptic integrals [1].

For the constant phase, we note that $y \equiv 0$ for $k^2 = \lambda$ and becomes meaningless for $k^2 > \lambda$. This defines a bifurcation line from the normal to the constant phase, denoted by Γ_{I} in Fig. 1. Likewise, the SC solution vanishes for $\lambda = \frac{1}{4}$ and is meaningless for $\lambda < \frac{1}{4}$. This defines the bifurcation line Γ_{II} from the normal to the SC phase. For $k = 0$, $G_{\text{const}} < G_{\text{SC}}$, but G_{const} increases with k^2 . $G_{\text{const}} = G_{\text{SC}}$ for

$$k^2 = \frac{1}{4} + (1 - \sqrt{2/3})(\lambda - \frac{1}{4}) - (\lambda - \frac{1}{4})^2 / \sqrt{486} + 5(\lambda - \frac{1}{4})^3 / 54^{3/2} + \dots \quad (18)$$

Except for the point $P = (k^2 = \frac{1}{4}, \lambda = \frac{1}{4})$, where $G_{\text{const}} = G_{\text{SC}} = 0$, equation (18) describes a line in the region $k^2 > \frac{1}{4}$. Therefore, the global minimizer in the relevant region is the constant phase.

Let us check now whether there are bifurcations from the constant phase. For this purpose, let us anticipate the nonuniform case and write

$$D = 1 + \epsilon D_1(\theta) \quad (19)$$

where ϵ is a small positive number and the deviation from uniformity is defined such that $\int_0^{2\pi} D_1(\theta) d\theta = 0$. Expanding the order parameter in the form

$$w = 1 - k^2/\lambda + \epsilon w_1 + \dots, \quad (20)$$

with $\lambda > k^2$, Eq. (11) gives to first order in ϵ a linear nonlocal differential equation for w_1 . The nonlocal term vanishes by periodicity, and we obtain

$$w_1'' + (6k^2 - 2\lambda)w_1 = -4k^2(1 - k^2/\lambda)D_1. \quad (21)$$

We note now that, even in the uniform case $D_1 \equiv 0$, (21) has nontrivial periodic solutions for $6k^2 - 2\lambda = n^2$, with n an integer. Nontrivial solutions for $n = 0$ are incompatible with the periodicity of the nonlocal equation and $6k^2 - 2\lambda = 1$ defines the line Γ_{IV} , where the constant solution bifurcates to solutions of EL that have a sinusoidal perturbation superimposed on the constant background. The cases $n > 1$ define lines which are far from the relevant region, and will not be considered.

There is still another bifurcation line which we know of. We shall see in Section 5 that at the line $k^2 = \frac{1}{4}$ there is a bifurcation from the SC phase. We denote this line by Γ_{III} .

We have verified numerically that in the region between Γ_{III} and Γ_{IV} there exists a solution of EL in addition to (13) and (15), which approaches continuously the SC and the constant solution at the respective bifurcation lines. This bridging solution is never a minimizer of G . The numerical procedure is described in Appendix B.

The point P at $\lambda = k^2 = \frac{1}{4}$ is a multiple point that sits at the intersection of four bifurcation lines. As a consequence, we expect EL to be highly degenerate at P. To get a better insight into the degeneracy, recall that near P one can assume that w is very small. Therefore we temporarily drop the cubic term in (11) (cf. (29) below). The modified equation has a three-parameter solution at P (for constant D):

$$w_P = A[1 - \gamma \cos(\theta - \theta_0)]. \quad (22)$$

The arbitrary phase θ_0 is due to the independence of D on θ , the arbitrary normalization A is due to the bifurcation at Γ_I or Γ_{II} , and $0 \leq \gamma \leq 1$ is due to the bifurcation at Γ_{III} and Γ_{IV} . Since Γ_{III} and Γ_{IV} cut each other, this family of solutions bridges between SC ($\gamma = 1$) and the constant solution ($\gamma = 0$) at a single point.

Our range of “interesting temperatures” focuses on the vicinity of P, i.e. where the coherence length is of the order of the diameter of the ring.

Let us now outline the case of nonuniform D . If D and w can be expressed by (19) and (20), then (21) can be solved by Fourier analysis. For conciseness, we take

$$D_1 = \sum_{n=1}^{\infty} \beta_n \cos n\theta. \quad (23)$$

Addition of odd terms is straightforward. We make the important observation that if D is of type S then D_1 has the form (23), with $\beta_1 < 0$. If D is not of type S , we still define $\beta_1 = \frac{1}{\pi} \int_0^{2\pi} D_1 \cos \theta d\theta$ and take $\beta_1 < 0$. Unless the first harmonic of D_1 vanishes, this choice of sign is just a choice of the origin of θ .

The solution of (21) is

$$w_1 = 4k^2 \left(1 - \frac{k^2}{\lambda}\right) \sum_{n=1}^{\infty} \frac{\beta_n \cos n\theta}{n^2 - 6k^2 + 2\lambda} . \quad (24)$$

This expansion provides an approximation for the order parameter in most of the relevant region, but is not valid near some of the bifurcation lines. We shall see that, due to the highly degenerate character of P , even an infinitesimal deviation from constant D has a profound influence on the phase diagram. We have cumulative evidence that, for nonuniform thickness, P splits and the phase diagram looks as in Fig. 2. In particular, there are regions where the doubly-connected phase resembles more the SC than the constant solution. The following sections are devoted to the justification of Fig. 2 to the study of $w(\theta)$ near the bifurcations.

We mention that in the phase diagrams (Figs. 1 and 2) we have marked only the two global minimizers we know of, singly and doubly connected. We have also met other qualitatively distinct solutions of EL, such as the “bridging solution” mentioned above, solutions with several oscillations, and solutions with a minimum where D is largest. As far as we have tested, these solutions are never global minimizers, and we do not report on them in detail.

An experimentally interesting quantity is the supercurrent. Far from the bifurcations we introduce (19) and (20) into (3) and note that D_1 and w_1 average to zero. We obtain

$$I = k\hbar\alpha e^*(\lambda - k^2)\overline{D}/(m^*\beta\lambda) + O(\epsilon^2), \quad (25)$$

where $\overline{D}$, the average of D , is now required. For fixed λ , this current attains its maximum value at $k = \sqrt{\lambda/3}$. Using the definition of λ , this maximum is, up to $O(\epsilon^2)$,

$$I_{\max} = \left(\frac{2\alpha}{3}\right)^{3/2} \frac{e^*\overline{D}}{\beta\sqrt{m^*}} . \quad (26)$$

4. BIFURCATIONS FROM THE NORMAL PHASE (N)

When $\lambda = 0$ and $k \neq 0$, the global minimizer is obviously $y \equiv 0$. Increasing λ , with fixed k , we expect to reach a critical value λ_c , corresponding to the critical temperature, at which the normal solution will bifurcate to a minimizer y_c which does not vanish identically. Here the subscript c stands for either I or II.

In order to perform the bifurcation analysis of (11), we introduce a small parameter η , and expand

$$\lambda = \lambda_c + \eta\lambda_{\eta 1} \dots, \quad w = \eta w_c + \eta^2 w_{\eta 2} + \dots \quad (27)$$

We also write an expansion for Λ

$$\Lambda^{-2} = \frac{\eta^2}{\Lambda_c^2} + \frac{2\eta^3}{\Lambda_c^3} \int_0^{2\pi} \frac{w_{\eta 2} d\theta}{D w_c^2} + \dots, \quad (28)$$

with $\Lambda_c \equiv \Lambda(w_c) = \int_0^{2\pi} (D w_c)^{-1} d\theta$. We thus obtain a sequence of equations for $w_c, w_{\eta 2}, \dots$. The leading order term w_c obeys

$$D w_c w_c'' + D' w_c w_c' - \frac{D}{2} (w_c')^2 + 2\lambda_c D w_c^2 - \frac{2}{D} \left(\frac{2\pi k}{\Lambda_c} \right)^2 = 0. \quad (29)$$

The second order term $w_{\eta 2}$ satisfies

$$L_\eta(w_{\eta 2}) = 2\lambda_c D w_c^3 - 2\lambda_{\eta 1} D w_c^2, \quad (30)$$

where the linear operator L_η is defined by

$$L_\eta(u) = D w_c u'' + (D' w_c - D w_c') u' + ((D w_c')' + 4\lambda_c D w_c) u - \frac{4(2\pi k)^2}{D \Lambda_c^3} \int_0^{2\pi} \frac{u d\theta}{D w_c^2}. \quad (31)$$

We remark that Equation (29) can be written in the form $L_\eta(w_c) = 0$. Notice also that (29) is invariant under multiplication of w_c by a constant.

We shall now study the curve $\lambda_c = \lambda_c(k)$, and the corresponding structure of w_c . Equation (29) is difficult to analyse, as it is nonlocal in a non-standard way. This difficulty can be overcome in the case of weakly nonuniform rings. We shall support our findings by solving (29) exactly, with arbitrarily large nonuniformities, for the case where D is piecewise constant. The high degeneracy near P implies that two types of expansion are needed. We shall first study the bifurcation from the normal state to the doubly connected phase away from P. The solution in the vicinity of P is postponed to Section 6. The bifurcation to the singly connected phase is a particularly simple case.

4.1 Bifurcation from Normal to DC

We are after a nontrivial solution of Equation (29). We choose the normalization such that

$$\int_0^{2\pi} w_c d\theta = 2\pi \quad (32)$$

and consider almost uniform thickness, given by (19). Using our knowledge for the case of constant D , we write $w_c = 1 + \epsilon w_1 + \epsilon^2 w_2 + \dots$ and $\lambda_c = k^2 + \epsilon \lambda_{c1} + \epsilon^2 \lambda_{c2} + \dots$. Expanding (29) and using (32), gives (to first order in ϵ)

$$w_1'' + 4k^2 w_1 = -2\lambda_{c1} - 4k^2 D_1. \quad (33)$$

Integrating and applying (32) and periodicity, we find that $\lambda_{c1} = 0$. Using (23), Fourier analysis of (33) gives

$$w_1 = \sum_{n=1}^{\infty} \frac{\beta_n \cos n\theta}{\frac{n^2}{4k^2} - 1}. \quad (34)$$

Except for normalization, this is the limit of (24) for $\lambda \rightarrow k^2$.

Expanding to second order in ϵ gives, after some manipulation,

$$\lambda_{c2} = \frac{k^2}{2} \sum_{n=1}^{\infty} \frac{\beta_n^2}{\frac{4k^2}{n^2} - 1}. \quad (35)$$

We see that, no matter how small ϵ is, the approximation scheme breaks down for $k^2 = \frac{1}{4}$. This was expected, since at this point Γ_1 intersects other bifurcation lines.

4.2 Bifurcation from Normal to SC

As in the previous subsection, λ_c is characterized by the fact that (9), or (11) without the term involving Λ , have a nontrivial solution, but the nonlinear term $\lambda D y^3$ or $2\lambda D w^3$ is negligible. It is easier to use the y formulation. Writing $y_c = y_0 + \epsilon y_1 + \epsilon^2 y_2 + \dots$ and $\lambda_c = \frac{1}{4} + \epsilon \lambda_{c1} + \epsilon^2 \lambda_{c2} + \dots$, we obtain a sequence of equations of the form

$$L_{\Pi}(y_0) = 0; \quad L_{\Pi}(y_i) = f_i, \quad (36)$$

where f_i is expressed in terms of the functions y_j with $j < i$ and

$$L_{\Pi}(y_i) \equiv y_i'' + \frac{1}{4} y_i. \quad (37)$$

L_{II} is linear and self adjoint in the space of functions that vanish at 0 and 2π , with inner product $(u, v) = \int_0^{2\pi} uv d\theta$. Therefore, f_i must fulfill Fredholm's condition [6] for solvability of the nonhomogeneous equation:

$$\int_0^{2\pi} f_i y_0 d\theta = 0. \quad (38)$$

This determines λ_{ci} . Taking D of type S and recalling the form (23) and the normalization (32), we obtain

$$\begin{aligned} y_0 &= \sqrt{2} \sin(\theta/2), \\ \lambda_{c1} &= \frac{1}{4} \beta_1, \\ y_1 &= -\frac{\sqrt{2}}{4} \sum_{n=1}^{\infty} \left(\frac{\beta_{n+1}}{n} + \frac{\beta_n}{n+1} \right) \sin((n + \frac{1}{2})\theta), \\ \lambda_{c2} &= \frac{3}{32} \beta_1^2 - \frac{1}{8} \sum_{n=2}^{\infty} \left[\frac{n^2}{n^2 - 1} \beta_n^2 + \beta_n \beta_{n-1} \right]. \end{aligned} \quad (39)$$

Note that, since $\beta_1 < 0$, $\lambda_c < \frac{1}{4}$.

4.3 Piecewise Constant Thickness - an Exact Solution

We note from (34) that the first harmonic diverges for $k^2 \rightarrow \frac{1}{4}$. Therefore, $w_1(0)$ will be a large negative quantity and, for k^2 sufficiently close to $\frac{1}{4}$, $\epsilon w_1(0)$ will not be small and the expansion of Subsection 4.1 breaks down. We conjecture that, for arbitrary nonuniformities that have a first harmonic component, $w(0)/\int_0^{2\pi} w d\theta$ becomes 0 as $k^2 \rightarrow \frac{1}{4}$ (along the line Γ_1). To support this conjecture and in order to have a test field for our approximations, we consider a special class of nonuniform rings, such that (29) can be solved exactly. In Section 6 we shall verify this conjecture for the case of weak arbitrary nonuniformities.

Let D have the form

$$D = \begin{cases} d & \theta < \pi/2 \\ 1 & \pi/2 < \theta < \pi \end{cases} \quad (40)$$

with $d < 1$, and D symmetric about $\theta = 0$ and about $\theta = \pi$. In each interval of the ring D is constant, so that differentiating (29) and dividing by w_c gives (in each interval)

$$w_c''' + 4\lambda_c w_c' = 0, \quad (41)$$

which has general solution of the form $w_c = A_i[1 - \gamma_i \cos 2\sqrt{\lambda_c}(\theta - \theta_i)]$. We are left with 7 parameters: A_i , γ_i , θ_i and λ_c . These are determined by normalization, by having the constant $(2\pi k/\Lambda_c)^2/D$ in (29) given by (5) in both intervals, and by continuity of w_c and Dw'_c at $\theta = \pi/2$ and $\theta = 3\pi/2$. Discontinuity of any of these quantities would lead to a divergence of w_c or w'_c (with the discontinuity in D regarded as the limit of a fast change).

Using the symmetry of the problem about 0 and π , using continuity of Dw'_c and the fact that $D^2(w_c w''_c + 2\lambda_c w_c^2)$ has the same value at $\theta = 0$ and $\theta = \pi$, taking $w_c(0) \leq w_c(\pi)$ and choosing a simple normalization, we write

$$w_c = \begin{cases} 1 - \gamma \cos 2\sqrt{\lambda_c}\theta & \theta < \pi/2 \\ d + d\gamma \cos 2\sqrt{\lambda_c}(\pi - \theta) & \pi/2 < \theta < \pi \end{cases} \quad (42)$$

The requirement of continuity of w_c is now

$$\gamma \cos(\pi\sqrt{\lambda_c}) = \frac{1-d}{1+d}. \quad (43)$$

Substituting (42) into (5) and (29) gives, after some trigonometric manipulations,

$$\pi k = \arctan\left(\sqrt{\frac{1+\gamma}{1-\gamma}} \tan \frac{\pi\sqrt{\lambda_c}}{2}\right) + \arctan\left(\sqrt{\frac{1-\gamma}{1+\gamma}} \tan \frac{\pi\sqrt{\lambda_c}}{2}\right). \quad (44)$$

Equations (43) and (44) determine the eigenvalue λ_c and $w_c(0) = 1 - \gamma$. The solution that describes the line Γ_I is

$$\lambda_c = \left[\frac{1}{\pi} \arcsin \left(\frac{2\sqrt{d}}{1+d} \sin \pi k \right) \right]^2 \quad (45)$$

$$\gamma = (1-d)/\sqrt{(1+d)^2 - 4d \sin^2 \pi k}. \quad (46)$$

For $k \rightarrow \frac{1}{2}$, (46) gives $\gamma \rightarrow 1$, that is, w_c vanishes at $\theta = 0$, which is the center of the thin portion of the ring. This confirms our conjecture. This situation describes the point P_1 in Fig. 2.

Writing $d = 1 - \epsilon$, assuming that k is bounded away from $\frac{1}{2}$, and expanding in ϵ gives $\lambda_c - k^2 = -(k/4\pi) \tan(\pi k) \epsilon^2$, $\gamma = \epsilon/(2 \cos \pi k)$, in agreement with Subsection 4.1. However, if we also write $k = \frac{1}{2} - \delta$ and take the limit $\epsilon \rightarrow 0$ with a fixed ratio δ/ϵ , then $\gamma = O(1)$. More precisely, we find $\gamma = 1/\sqrt{1 + (2\pi\delta/\epsilon)^2}$ and $\lambda_c - \frac{1}{4} = -\epsilon/(2\pi\gamma)$.

4.4 The Bifurcating Branch ($\lambda > \lambda_c$)

The operator L_η defined in (31) is self adjoint in the space of periodic functions under the inner product

$$(u, v) = \int_0^{2\pi} \frac{uv}{w_c^2} d\theta. \quad (47)$$

Therefore, application of Fredholm's condition to (30) gives

$$\lambda_{\eta 1} = \lambda_c \int_0^{2\pi} Dw_c^2 d\theta / \int_0^{2\pi} Dw_c d\theta. \quad (48)$$

This determines the value of η in (27). It is easy to show that (48) holds for the SC solution, too.

Substituting now (27) into (12) we find that to leading order the free energy is

$$- \frac{(\lambda - \lambda_c)^2 (\int_0^{2\pi} Dw_c d\theta)^2}{4\pi \lambda_c \int_0^{2\pi} Dw_c^2 d\theta}. \quad (49)$$

5. BIFURCATIONS FROM THE SINGLY CONNECTED PHASE

The present section deals with an essential property of our model, and the main results are valid for arbitrary shape of $D(\theta)$, i.e., the nonuniformity in the thickness is not necessarily small. For simplicity, we shall assume again that D is of type S .

In the SC solution $w(0) = 0$ and near a bifurcation from it $w(0)$ is small. The existence and nature of the bifurcations from the SC solution stem from the divergence of Λ as $w(0) \rightarrow 0$.

Let us first assume that $D(\theta)$ is smooth in the region near $\theta = 0$. Let us write for shorthand

$$f(\theta) = D(\theta)w(\theta), \quad \tilde{f}(\theta) = f(0) + \frac{1}{2}f''(0)\theta^2, \quad (50)$$

where we have used the symmetry of the problem to include only even powers of θ , and let us separate Λ into a divergent and a regular part:

$$\frac{1}{2}\Lambda = \int_0^\infty \frac{d\theta}{\tilde{f}} + \frac{1}{2}\Lambda_R, \quad (51)$$

with

$$\frac{1}{2}\Lambda_R = - \int_\pi^\infty \frac{d\theta}{\tilde{f}} + \int_0^\pi \frac{\tilde{f} - f}{f\tilde{f}} d\theta. \quad (52)$$

Λ_R remains finite for $w(0) \rightarrow 0$. Performing the integration in (51),

$$\Lambda = \frac{\pi}{\sqrt{\frac{1}{2}f(0)f''(0)}} + \Lambda_R. \quad (53)$$

We set now $\theta = 0$ in (11), note that $w'(0) = 0$, introduce (53) and (50), and expand to order $w(0)^{1/2}$. This gives

$$\sqrt{2w(0)w''(0)}D(0)\Lambda_R = \pi(1 - (2k)^{-2}). \quad (54)$$

The bifurcation line is obtained by taking $w(0) \rightarrow 0$. This gives $k = \frac{1}{2}$, independently of λ .

If $\Lambda_R > 0$ (resp. $\Lambda_R < 0$), then (54) can be satisfied with $w(0) > 0$ only for $k^2 > \frac{1}{4}$ (resp. $k^2 < \frac{1}{4}$). We can therefore expect that for $\Lambda_R < 0$ there is a bifurcation from the SC to the DC phase and, for $\Lambda_R > 0$, to the bridging solution in the irrelevant region. Numerical solution of (11) for $k^2 \approx \frac{1}{4}$ and various values of λ confirms this scenario.

If the thickness is almost uniform, $w(\theta)$ in the SC phase can be approximated by means of (39) and (30). Once w is known, Λ_R can be evaluated. Keeping one correction term in ϵ and in η , we obtain

$$\Lambda_R = \frac{\pi}{2} \left(1 + \frac{3\epsilon\beta_1\lambda_c}{\lambda - \lambda_c} \right). \quad (55)$$

Recalling that $\beta_1 < 0$, we see that $\Lambda_R < 0$ for λ sufficiently close to λ_c , but eventually changes sign at a point which we may identify as P_2 in Fig. 2. Taking λ_c from (39), we find that P_2 is located at $\lambda = \frac{1}{4} - \epsilon\beta_1/2$.

If the thickness is uniform, then $\Lambda_R = 0$ at P and is positive for $\lambda > \lambda_c$, in agreement with Fig. 1.

Let us finally discuss the case where $D'(\theta)$ is discontinuous at $\theta = 0$, as in the example of Ref. [3]. Due to the continuity of Dw' , the discontinuity of $f'(\theta)$ will be of order $w(0)$. The same will be true for the coefficient of θ^3 in the expansion of f . Therefore, (50) can still be used and (52) does not diverge as $w(0) \rightarrow 0$.

6. THE REGION NEAR THE CRITICAL POINTS

We shall again restrict ourselves to the case where D is almost uniform (cf. (19)), define $\delta = \frac{1}{4} - k^2$ and $\lambda_1 = (\lambda - \frac{1}{4})/\epsilon$, and expand around the point P:

$$w = \eta(w_P + \epsilon w_1 + \dots). \quad (56)$$

The expansion is in powers of ϵ only, but we explore the region where λ_1 , δ/ϵ and η/ϵ are finite and the terms in the expansion depend on these parameters. The leading order term w_P is given by the expression (22), where without loss of generality we set $A = 1$ and the other parameters are still undetermined. At this stage it will be instructive to consider D which is not necessarily symmetric about 0 and π .

Substituting (56) into (11) leads to the equation $L_P(w_1) = f_1$, with

$$L_P(u) \equiv w_P u'' - w_P' u' + u - \frac{\Delta^{3/2}}{2\pi} \int_0^{2\pi} \frac{u}{w_P^2} d\theta, \quad (57)$$

$$f_1 = -\Delta D_1 - w_P w_P' D_1' - 2\lambda_1 w_P^2 + \frac{\eta}{2\epsilon} w_P^3 + \frac{\Delta^{3/2}}{2\pi} \int_0^{2\pi} \frac{D_1}{w_P} d\theta - 2\Delta \frac{\delta}{\epsilon}, \quad (58)$$

and $\Delta = 1 - \gamma^2$.

As in the situations considered above, L_P is linear and self adjoint under the inner product $(u, v) = \int_0^{2\pi} (uv/w_P^2) d\theta$. Also, it is easy to check that $L_P(w_P) = 0$. The unusual feature is that there are other solutions as well, that is, $\text{Ker}(L_P)$ is not one dimensional. In fact, $\text{Ker}(L_P)$ is three dimensional. It is spanned by the three functions $\{1, w_P, w_P'\}$, corresponding to the three parameters in w_P .

Therefore we obtain a set of three solvability conditions

$$\int_0^{2\pi} \frac{f_1}{w_P^2} d\theta = \int_0^{2\pi} \frac{f_1}{w_P} d\theta = \int_0^{2\pi} \frac{f_1 w_P'}{w_P^2} d\theta = 0. \quad (59)$$

The last condition implies

$$\int_0^{2\pi} D_1 \sin(\theta - \theta_0) d\theta = 0. \quad (60)$$

This equation determines the position $\theta = \theta_0$ at which w_P has a minimum and may eventually vanish. Note that θ_0 is determined by the geometry only, and does not vary with the temperature or the magnetic field. After having obtained (60), we can redefine θ and set $\theta_0 = 0$ without loss of generality.

The other two conditions in (59) reduce to

$$\lambda_1 + \Delta^{-1/2} \frac{\delta}{\epsilon} = \frac{\eta}{4\epsilon} \quad (61)$$

and

$$4\lambda_1 + 4\Delta^{1/2} \frac{\delta}{\epsilon} - \gamma\beta_1 - (1 + \frac{1}{2}\gamma^2) \frac{\eta}{\epsilon} = 0. \quad (62)$$

These two equations determine γ and η . The following formula that can be derived from (61)-(62) will be useful later on:

$$\frac{\eta}{\epsilon} = \frac{8\lambda_1}{3} - \frac{2\beta_1}{3\gamma}. \quad (63)$$

6.1 The Bifurcation Line Γ_1 Near the Point P_1

This is obtained by setting $\eta = 0$ in (62) and (61). The lowest value of λ for which both equations are fulfilled is obtained for

$$\lambda_1 = \lambda_{c1} = -\frac{1}{4} \sqrt{\beta_1^2 + (4\delta/\epsilon)^2}, \quad (64)$$

and

$$\gamma = -\frac{\beta_1}{\sqrt{\beta_1^2 + (4\delta/\epsilon)^2}} = \frac{\beta_1}{4\lambda_{c1}}. \quad (65)$$

The limit considered at the end of Subsection 4.3 is a special case of (65), with $\beta_1 = -2/\pi$. It is also interesting to note that (64) can be extrapolated to the case that δ is not small and it still reproduces to order ϵ the result obtained for λ_c in Subsection 4.1.

We note that no matter how small ϵ is, i.e. even for arbitrarily weak nonuniformities, $\gamma \rightarrow 1$ as $\delta \rightarrow 0$. Hence we deal here with a pattern selection mechanism, where the SC pattern is selected among all the infinitely many solutions (22).

6.2 Evaluation of w_1

For conciseness, we shall again consider D of the form (23). Fourier analysis of the equation $L_P(w_1) = f_1$ and use of (63) yield

$$w_1 = \sum_{n=0}^{\infty} a_n \cos n\theta$$

with

$$a_2 = \frac{\gamma\beta_1}{3} + \frac{\beta_2}{3} - \frac{\gamma\beta_3}{4} - \frac{\gamma^2\lambda_1}{3}$$

and

$$a_n = \frac{\gamma}{2n}(\beta_{n-1} - \beta_{n+1}) + \frac{\beta_n}{n^2 - 1} \quad (66)$$

for $n \geq 3$. The coefficients a_0 and a_1 remain undetermined to the present order in the expansion (56); this is the same situation we met in Eq. (22), where A and γ remained undetermined.

6.3 The Region Near the Point P_2

We know from Section 5 that near $(k^2 = \frac{1}{4}, \lambda = \frac{1}{4} - \epsilon\beta_1/2)$ there is a special point. The goal of this subsection is to obtain the behavior of $w(0) \approx \eta w_P(0)$ near this point. For this purpose we eliminate η from (61) and (62) and substitute $\gamma = 1 - w_P(0)$. This gives an equation for $w_P(0)$:

$$\frac{\delta}{\epsilon} = \frac{1}{3} \frac{\sqrt{2 - w_P(0)}}{1 - w_P(0)} w_P(0)^{1/2} (\lambda_1 w_P(0) - (\lambda_1 + \frac{\beta_1}{2})). \quad (67)$$

Near P_2 , $w_P(0) \ll 1$, hence it is negligible compared to 1 or 2. However, in the relevant regime $\lambda_1 w_P(0)$ is of the same order as $\lambda_1 + \beta_1/2$. Therefore, (67) becomes a third degree equation for $w_P(0)^{1/2}$. The solution of this equation provides the missing information about $w(\theta)$ to present order in the region near P_2 .

We see from (67) that the relevant region $\frac{1}{4} - k^2 = \delta \geq 0$ corresponds to $w_P(0) \geq 1 + \beta_1/(2\lambda_1)$. In order to characterize the solutions of (67), we have drawn in Fig. 3 a contour plot of $\delta(w_P(0), \lambda_1)$. At the axis $w_P(0) = 0$, $\delta = 0$. For $\lambda_1 < -\beta_1/2$, all the factors in (67) are positive, δ increases monotonically with $w_P(0)$, and there is only one $w_P(0)$ for a given δ . However, for $\lambda_1 > -\beta_1/2$, there is initially a valley into the irrelevant region, that is, δ is negative - a situation which cannot correspond to the minimal energy. The level $\delta = 0$ is reached again for $w_P(0) = 1 + \beta_1/(2\lambda_1)$, and this is found to be the global minimizer. This situation corresponds to the ray to the right of P_2 in Fig. 2. The line Γ_{IV} is characterized by $\frac{\partial \delta}{\partial w_P(0)} = 0$; this happens at $\delta/\epsilon \approx -(1/(3\sqrt{\lambda_1}))(2(2\lambda_1 + \beta_1)/3)^{3/2}$.

6.4 Higher Order Treatment

The first order expansion in (56) leaves the 0th and 1st harmonic of $w(\theta)$ undetermined for the doubly connected phase. This may not be a grave shortcoming, unless they diverge and their contribution is actually of $O(1)$. We might especially suspect that the behavior of the entire $w(0)$ near P_2 is qualitatively different from that of $w_P(0)$. We therefore proceed to evaluate these harmonics near P_2 .

In order to keep the analysis simple, we now restrict ourselves to $D(\theta)$ of the form $D = 1 + \epsilon\beta_1 \cos \theta$ with $(\beta_1 < 0)$. Cases of nonuniformities that are neither smooth nor small will be reported elsewhere. Using (56), (63) and (66) sufficiently close to $k^2 = 1/4$, $\lambda_1 = -\beta_1/2$ and recalling that $\gamma = 1$ at P_2 , we can write

$$w = -2\beta_1\epsilon(1 + p\epsilon - \cos \theta)(1 + q\epsilon - \beta_1\epsilon \cos \theta) + O(\epsilon^3), \quad (68)$$

with $p = a_0 + a_1 + \beta_1/2$ and $q = -a_1 - \beta_1$. Our strategy is now to use (68) without the correction term as a variational form, and to find the parameters p and q that minimize G in (10). Since $w(0)$ is proportional to p , we are especially interested in the behavior of $p(\lambda_1, \delta)$ at this minimum.

Eq. (10) contains two integrals that require careful handling. One of them is $\int D(w')^2/wd\theta$, which contains a vanishing denominator for $p\epsilon \rightarrow 0$. In this case we perform the integral without taking $p\epsilon$ as a small quantity, and expansion on it is performed only after the integration.

The second delicate integral is Λ . Using the periodicity and the behavior of $\cos \theta$ in the complex plane, we can write $\Lambda = \int (wD)^{-1}d\theta$, where the integral is around the rectangle with vertices at $-\pi/2$, $3\pi/2$, $3\pi/2 + \infty i$ and $-\pi/2 + \infty i$. Since wD is the product of three simple factors, it is easy to find the poles and residues of the integrand, and Λ can be evaluated exactly.

We write now $k^2 = \frac{1}{4} - \delta$, with $\delta/\epsilon^{2.5} < C < \infty$, $\lambda = 1/4 - \epsilon\beta_1/2 + \epsilon^2\tilde{\lambda}$, and expand G up to $O(\epsilon^3)$. We obtain a polynomial in $\sqrt{p}$ and q . Minimizing this expression gives

$$8\tilde{\lambda} + 2\beta_1(2p + 3q) - 9\beta_1^2 = 0 \quad (69)$$

and

$$\frac{\delta}{\epsilon^{2.5}} = \frac{\sqrt{2}}{3}p^{1/2}\left(-\frac{\beta_1}{2}p - \tilde{\lambda} + \frac{3\beta_1^2}{8}\right). \quad (70)$$

One immediately recognizes that (70) describes the same behavior as (67), but the point P_2 is shifted to

$$\lambda_{P_2} = \frac{1}{4} - \frac{1}{2}\epsilon\beta_1 + \frac{3}{8}(\epsilon\beta_1)^2. \quad (71)$$

7. DISCUSSION

We have analytically obtained the phase diagram in the entire temperature-magnetic flux plane, as schematically drawn in Fig. 2. Some of our results are valid for small deviations from uniform thickness, some results are valid for arbitrary shape of $D(\theta)$ and some are valid for piecewise constant thickness; nevertheless, all the results are consistent among themselves and with Fig. 2. In addition, we have numerically tested the predicted dependence of the minimum value $w(0)$ of the order parameter as the physical parameters λ and k are varied. An integrative look of all the cases considered makes it reasonable to expect that the results found here will remain qualitatively correct for almost any form of the thickness $D(\theta)$.

The results obtained here enable us to check the numerical findings obtained in Ref. [3] for $k^2 = \frac{1}{4}$ and for a particular form of $D(\theta)$. In [3] we compared the free energies of the SC and the DC phases. Upper bounds for these free energies were obtained by using sequences of Padé approximants of increasing length as variational forms. $\tilde{G}$ in equation (6) was minimized in the space of the coefficients of these approximants. In [3] we did not suspect that the DC phase goes continuously into the SC phase at the line Γ_{III} . Since at this line both phases become the same, our previous approach was clearly inappropriate. Indeed, there is a region in which the singly-connected phase is thermodynamically favorable. We also confirm here that along the line $k^2 = \frac{1}{4}$ there are *two* phase transitions as the temperature is varied below T_c . However, the transition at P_2 is not discontinuous (first order), as concluded from our early numerical results, but rather a continuous (second order) transition after which $w(0)$ increases at the rate $dw(0)/d\lambda = 4$.

In the relevant region ($k^2 \leq \frac{1}{4}$) the stability domain of the singly-connected phase is restricted to a line segment, and has measure zero. This property might have applications for calibration purposes. However, the transition to the doubly-connected phase is continuous, and near this segment $w(0)$ will be small.

A simple experimental verification of our predictions could be performed by measuring the supercurrent by means of a magnetometer, as in Ref. [10]. Fig. 4 shows numerical evaluations of the supercurrent, given by (3), as functions of the magnetic flux for three different temperatures close to P_2 .

Another experimental verification of our predictions could be obtained by detecting the current fluctuations [9]. In the doubly-connected phase, for $\lambda > \lambda_{P_2}$, the supercurrent does not vanish when the flux is a half-integer number of quanta ($k^2 = \frac{1}{4}$). As a consequence, this situation is degenerate, since the supercurrent can flow in either sense. Near P_2 , the energy barrier between both minima of G is small, and the supercurrent fluctuates. However, for $\lambda \leq \lambda_{P_2}$ the supercurrent vanishes, and fluctuations should disappear, while the sample remains superconducting.

A third way to detect whether G has one or two minima is by the absence or presence of hysteresis as the magnetic field is varied: for $\lambda > \lambda_{P_2}$, if the flow Φ is slowly raised and crosses a half integer of quanta Φ_0 , then according to (4) and (7), k ought to jump from $\frac{1}{2}$ to $-\frac{1}{2}$ in order to minimize the free energy. Following (3) and (2), this implies a jump in the order parameter. Since the order parameter stays in a local minimum of the free energy and the sample ‘does not know’ that there is a still lower minimum, the jump in the order parameter and the inversion of I may occur only after k is larger than $\frac{1}{2}$. If the change in Φ is now reversed, the order parameter will jump back at a lower value of Φ , after k is smaller than $\frac{1}{2}$. We argue that this hysteresis phenomenon should not occur for $\lambda \leq \lambda_{P_2}$. Although at $k = \pm\frac{1}{2}$ there is still a jump in the phase ϕ , equation (2) suggests that this jump concentrates where u vanishes, and is thus not physically observable.

Our analysis for almost uniform thickness shows that the important part of the nonuniformity is its first harmonic. This might explain why the effects predicted here were not observed in [10] for samples with a weak link (a small region where $D(\theta) \ll 1$), which might be thought to be extremely nonuniform. When the deviation from uniformity is not small, Eq. (39) suggests that coupling between different harmonics becomes important.

From a mathematical point of view, the the Little-Parks problem poses a nonstandard

minimization problem:

$$\text{Min } G[y; k] = \int_0^{2\pi} (y')^2 D d\theta + (2\pi k)^2 \Lambda^{-1} \quad (72)$$

subject to the constraint $\int_0^{2\pi} y^2 D d\theta = 1$. It might appear that this is a very specific problem, but it actually stems from very general principles: the Ginzburg-Landau equation (which is nothing but a slowly varying small order parameter expansion), conservation of current and single-valuedness of the order parameter. In general, for a multiply connected sample, we shall have a problem with a larger parameter-space. Instead of one k we shall have a k_i for each hole in the sample that can enclose a flux and we shall have a Λ_i for the supercurrent around that hole.

ACKNOWLEDGMENT

This research was supported by the US-Israel Binational Science Foundation. J. B. was also supported by GIF and DFG.

References

- [1] M. Abramowitz and I.A. Stegun, *Handbook of Mathematical Functions*, U.S. Nat. Bureau of Standards (1964).
- [2] A.A. Abrikosov, *Fundamentals of the Theory of Metals*, North Holland (1988).
- [3] J. Berger and J. Rubinstein, “Topology of the order parameter in the Little-Parks experiment”, *Phys. Rev. Lett.* *75*, 320-322, 1995.
- [4] S.J. Chapman, S.D. Howison and J.R. Ockendon, “Macroscopic models for superconductivity”, *SIAM Review* *34*, pp. 529-560, 1992.
- [5] Q. Du, M.D. Gunzburger and J. S. Peterson, “Analysis and approximation of the Ginzburg Landau model of superconductivity”, *SIAM Review* *34*, pp. 54-81, 1992.
- [6] J. P. Keener, *Principles of Applied Mathematics*, Addison Wesley (1988).
- [7] L.D. Landau and E.M. Lifshitz, *Statistical Physics*, Pergamon Press (1980).
- [8] W.A. Little and R.D. Parks, “Observation of quantum periodicity in the transition temperature of a superconducting cylinder” *Phys. Rev. Lett.* *9*, 9-12, 1962.
- [9] J.E. Lukens and J.M. Goodkind, “Flux fluctuations and critical currents in a superconducting ring near T_c ”, *Phys. Rev. Lett.* *20*, pp. 1363-1365, 1968.
- [10] A.H. Silver and J.E. Zimmerman, “Quantum states and transitions in weakly connected superconducting rings”, *Phys. Rev.* *157*, pp. 317-341, 1967.
- [11] M. Tinkham, *Introduction to Superconductivity*, Krieger, Malabar (1980).

Appendix A. Influence of the Expelled Flux

We deal now with the contribution of the term $(H - H_{\text{ext}})^2$ in (1), which has so far been neglected. Let us first consider the case where the sample is a long circular cylinder. Then it is well known that $H - H_{\text{ext}} = 4\pi I/(hc)$, where $h \gg R$ is the height of the cylinder. This additional magnetic field exists inside the cylinder, i.e., in a volume $\pi R^2 h$. Therefore, its contribution to G is

$$G_H = 4k^2 \pi^3 \kappa^{-2} h^{-1} \lambda \Lambda^{-2} / \int_0^{2\pi} D d\theta, \quad (73)$$

where we have used (3), $R = 1$, and $\kappa = \lambda_L/\xi$ is the Ginzburg-Landau parameter. Note that G_H is proportional to the thickness D/h , and we are no longer free to choose the normalization of D .

If the sample is not a long cylinder, then G_H has to be divided by the self-inductance of the cylinder and multiplied by the actual self-inductance of the sample. For simplicity, let us stick to (73). The influence of G_H in the EL equation is that the nonlocal term in (11) is multiplied by the factor $(1 + 2\pi\kappa^{-2}h^{-1}\lambda\Lambda^{-1})$. Therefore, a sufficient condition for this correction to be unimportant is $\kappa^{-2}\lambda D/h \ll R$.

We are mainly interested in the influence of G_H when Λ diverges. Following the steps of Section 5, we reach again (54), but Λ_R has to be replaced by $\Lambda_R - \pi\lambda/(h\kappa^2)$. Therefore, the bifurcation from SC is still along the line $k^2 = \frac{1}{4}$, but the point P_2 moves to higher values of λ .

Appendix B. Numerical Solution of Equation (11)

We used the built-in MATHEMATICA functions. The procedure is as follows.

1. Fix $w(0)$, λ and $C = 2(2\pi k/\Lambda)^2$.
2. With these values fixed, we can use NDSolve to evaluate $w(\theta)$. This function requires the initial values of w . $w(0)$ is given and $w'(0) = 0$. One has to be careful not to pick values of C which are too large, since they lead to $w(\pi) \gg 1$.

3. The true value of C is now obtained by requiring periodicity. If w is expected to be of type S , we can use the function FindRoot to require, for instance, that $w(3) - w(2\pi - 3) = 0$. (This difference is now regarded as a function of C .)
4. After the true C and the corresponding $w(\theta)$ are known, we obtain Λ by numeric integration. We then evaluate $k^2 = C\Lambda^2/(8\pi^2)$. In this way we obtain k^2 as a function of λ and $w(0)$.

Figure B1 shows a sequence of solutions of equation (11) with varying values of $w(0)$.

Figure Captions

Fig. 1: Phase diagram for a ring of uniform thickness. λ is proportional to $T_c - T$ and k measures the deviation from an integer number of magnetic flux quanta. The dashed lines denote bifurcations between solutions of the Euler-Lagrange equation which are not global minimizers. The line with uneven dashing denotes first order (discontinuous) transition between the singly and the doubly connected phases.

Fig. 2: Phase diagram when the thickness is not uniform. P splits into two critical points, P_1 and P_2 , and the portion of the the bifurcation line Γ_{III} between these points is physically relevant.

Fig. 3: Contour plot of $\delta = \frac{1}{4} - k^2$. δ increases toward the lower right. At the upper left there is a “valley”, where $\delta < 0$. The line Γ_{IV} in Fig. 2 “goes down” along this “valley”.

Fig. 4: Supercurrent as a function of k for several values of the parameter $\lambda = (R/\xi)^2$. For $\lambda \leq \lambda_{P_2}$, the supercurrent vanishes at $k = \frac{1}{2}$. For $\lambda = \lambda_{P_2}$, the supercurrent rises with infinite slope. For larger λ , $I(\frac{1}{2}) \neq 0$. I_{max} is given by Eq. (26).

Fig. B1: $w(\theta)$ and k as functions of $w(0)$. The value obtained for k is shown next to the corresponding curve. For the present illustration we took uniform D and $\lambda = 1$. This is the “bridging solution”, discussed in Section 3. The extreme situations were taken from (13) and (15). If D is weakly nonuniform and $k \neq 0$, then the DC phase looks qualitatively as this bridging solution.